A large, thick, grey circular arrow graphic that starts at the top right, goes down, then left, then up, and finally right, ending at the top right. It frames the text inside.

12/1/82
DATE _____

SSC Service Bulletin
82-285
no. _____

TO: ALL REGENCY COMMUNICATIONS PROFESSIONAL SALES AND SERVICE CENTERS
ALL REGENCY COMMUNICATIONS PROFESSIONAL SALES REPRESENTATIVES

SUBJECT: MA-187 INSTALLATION INSTRUCTION MANUAL ADDITION

Service Manual Changes:

Add Pages 9, 10, and 11 to your MA-187 Installation Instruction Manual, P/N 7001-4192-500. These pages cover installation of the MA-187 into the TRPU-102 Series radios.

TECHNICAL SERVICE DEPARTMENT
REGENCY COMMUNICATIONS, INC.

MA-187 - INSTALLATION INSTRUCTIONS FOR TRPU SERIES RADIOS

Using 7 conductor ribbon cable supplied with the MA-187, connections are as follows: (Refer to Figure 7)

<u>Wire Color</u>	<u>Connect to</u>	<u>Function</u>
1. Brown	Ground	Ground
2. Red	P5	+7.5 VDC
3. Orange	Series 100K* resistor to IC300, Pin 3 (U2)	Encode output
4. Yellow	A3	Audio filter output
5. Green	A2	Audio filter input
6. Blue	K5	Tone squelch enable
7. Violet	K10	Squelch Switch

*100K ohm resistor supplied with MA-187.

MA-187 INSTALLATION INSTRUCTIONS FOR
TRPU-102 SERIES RADIOS





FIGURE 7

NOTE:

1.) CUT JU-200



MA 187 PREP FOR INSTALLATION
IN TRPU 102

FIGURE 8

